

OFF-GRID **Omega Series** UM v4 3K-24 OFF-GRID INVERTER

- Customizable status LED ring with RGB lights.
- Touchable button with 4.3" colored LCD.
- Built-in Wifi for mobile monitoring (App is available).
- Supports USB On-the-Go function.
- Data log events stored in the inverter.
- Reserved communication port (RS485, CAN-BUS or RS232) for BMS.
- · Battery independent design.
- Battery equalization extends lifecycle.
- User-friendly LCD operation.
- · Enhanced charging power.
- Built-in anti-dust kit.

User-programmable RGB lighting for different operation mode



Three lighting effects



Illuminates with twinkling lights in a color of your choice.

Chasing Radiates your selected color upward from the bottom of the ring.



Área Industrial La Dehesa - C/ Dehesa Vieja, 2 - 28052 Madrid (Spain) Tel. (+34) 918 021 649 - Fax. (+34) 917 750 542 info@masterbattery.es - www.masterbattery.es/en



Rated Power	3600 VA / 3600 W
INPUT	
Voltage	230 VAC
Voltage	170 - 280 VAC (For Personal Computers);
Selectable Voltage Range	
	90 - 280 VAC (For Home Appliances)
Frequency Range	50 Hz / 60 Hz (Auto sensing)
OUTPUT	
AC Voltage Regulation (Batt. Mode)	230 VAC ± 5%
Surge Power	7200 VA
Efficiency (Peak)	90% ~ 93%
Transfer Time	15 ms (For Personal Computers);
	20 ms (For Home Appliances)
Waveform	Pure sine wave
BATTERY	
Battery Voltage	24 VDC
Floating Charge Voltage	27 VDC
Overcharge Protection	33 VDC
SOLAR CHARGER & AC CHARGER	
Solar Charger Type	MPPT
Maximum PV Array Power	4000 W
MPPT Range @ Operating Voltage	120 ~ 450 VDC
Max. PV Array Open Circuit Voltage	500 VDC
Maximum Solar Charge Current	120 A
Maximum AC Charge Current	100 A
Maximum Charge Current	120 A
PHYSICAL	
Dimension, D x W x H (mm)	115 x 300 x 400
Net Weight (kg)	9.0
Communication Interface	USB / RS232 / RS485 / WiFi / Dry-contact
OPERATING ENVIRONMENT	
Humidity	5% to 95% Relative Humidity (Non-condensing)
Operating Temperature	-10°C to 50°C
Storage Temperature	-15°C to 60°C

Product specifications are subject to change without further notice.

