

ZXM7-SHW144 Series

10BB HALF-CELL Monocrystalline PERC Lightweight-reinforced PV Module

520-550W **21.46**%


0.60%

POWER RANGE MAXIMUM EFFICIENCY **YEARLY DEGRADATION**









KEY FEATURES-



More Elegant

Module's surface is smoothness, does not distort, no have spot.



More Safe

Absolutely no have self-detonate problem.



Excellent Cells Efficiency

MBB technology reduce the distance between busbars and finger grid line which is benefit to power increase.



Excellent Quality Managerment System

Adapt To Harsh Outdoor Environment

Resistant to harsh environments such as salt, ammonia, sand, high temperature and high humidity environment.

Better Weak Illumination Response

cloudy, and early morning.

More power output in weak light condition, such as haze,

Warranted reliability and stringent quality assurances well beyond certified requirements.





Anti PID

Ensured PID resistance through the quality control of cell manufacturing process and raw materials.



DIMENSIONS OF PV MODULE(mm)






I-V CURVES OF PV MODULE(530W)

P-V CURVES OF PV MODULE(530W)

Voltage [V]



ELECTRICAL CHARACTERISTICS | STC*

Nominal Power Watt Pmax(W)*	520	525	530	535	540	545	550
Maximum Power Voltage Vmp(V)	40.60	40.80	41.00	41.20	41.40	41.60	41.80
Maximum Power Current Imp(A)	12.82	12.88	12.94	13.00	13.05	13.11	13.16
Open Circuit Voltage Voc(V)	48.90	49.10	49.30	49.50	49.70	49.90	50.10
Short Circuit Current Isc(A)	13.54	13.60	13.66	13.72	13.78	13.84	13.90
Module Efficiency (%)	20.29	20.49	20.68	20.88	21.07	21.27	21.46

^{*}The data above is for reference only and the actual data is in accordance with the pratical testing

MECHANICAL DATA

Solar cells	Mono PERC
Cells orientation	144 (6×24)
Module dimension	2272×1128×2.5 mm (Frameless,JB Included)
Weight	13.5 ±1.0 kg
Glass	1.6mm,Float heat strengthened glass
Junction box	IP 68, 3 diodes
Cables	4 mm ² ,350 mm (With Connectors)
Connectors*	MC4-compatible

^{*}Please refer to regional datasheet for specified connector

ELECTRICAL CHARACTERISTICS | NMOT

388.90	392.60	396.30	400.00	403.50	407.20	410.80
37.80	38.00	38.20	38.30	38.50	38.70	38.90
10.29	10.34	10.39	10.43	10.48	10.52	10.57
45.70	45.90	46.10	46.20	46.40	46.60	46.80
10.94	10.98	11.03	11.08	11.13	11.18	11.22
	37.80 10.29 45.70 10.94	37.80 38.00 10.29 10.34 45.70 45.90 10.94 10.98	37.80 38.00 38.20 10.29 10.34 10.39 45.70 45.90 46.10 10.94 10.98 11.03	37.80 38.00 38.20 38.30 10.29 10.34 10.39 10.43 45.70 45.90 46.10 46.20	37.80 38.00 38.20 38.30 38.50 10.29 10.34 10.39 10.43 10.48 45.70 45.90 46.10 46.20 46.40 10.94 10.98 11.03 11.08 11.13	10.29 10.34 10.39 10.43 10.48 10.52 45.70 45.90 46.10 46.20 46.40 46.60 10.94 10.98 11.03 11.08 11.13 11.18

^{*}NMOT:Irradiance 800W/m²,Ambient Temperature 20°C,AM 1.5,Wind Speed 1m/s

PACKAGING CONFIGURATION*

Piece/Box 46
Piece/Container(40'HQ) 736

*Customized packaging is available upon request.

TEMPERATURE RATINGS

NMOT	44°C ±2°C	Maximum system voltage	1500 V DC
Temperature coefficient of Pmax	-0.35%/℃	Operating temperature	-40°C~+85°C
Temperature coefficient of Voc	-0.29%/℃	Maximum series fuse	25 A
Temperature coefficient of Isc	0.05%/℃	Front Side Maximum Static Loading	Up to 5400 Pa
		Rear Side Maximum Static Loading	Up to 2400 Pa

WORKING CONDITIONS

🍳 Add : 1#, Zhixi Industrial Zone, JintanJiangsu 213251, P.R. China 🔍 Tel: +86 519 6822 0233 🖂 E-mail: info@znshinesolar.com

Front View

^{*}Remark: customized cable length available upon request

^{*}STC (Standard Test Condition): Irradiance 1000W/m², Module Temperature 25±2°C, AM 1.5

^{*}Measuring uncertainity: ±3%, all the electrical characteristics such as Power, Im, Vm and FF are within ±3% tolerance.

^{*}Remark:Do not connect Fuse in Combiner Box with two or more strings in parallel connection

^{*}Remark: Electrical data in this catalog do not refer to a single module and they are not part of the offer.

They only serve for comparison among different module types.

^{*}Caution:Please be kindly advised that PV modules should be handled and installed by qualified people who have professional skills and please carefully read the safety and installation instructions before using our PV modules.